

A1 Microwave

Web: <http://www.A1Microwave.com>

Email: A1sales@A1Microwave.com



A1 Microwave is a leading designer and manufacturer of filters, diplexers, power combiners, couplers and adaptors for satcoms, telecoms, radar, medical and scientific applications.

A1 Microwave also provides standard and custom waveguide components and assemblies including : straights, bends, twists and flexibles.

A1 Microwave is ITAR free and provides a **Fast delivery and No NRE** (on standard designs) by using sophisticated in-house design and simulation software, all new **designs are "right first time"** allowing the design to move from the design computer to the machine shop without the need for prototyping. **Stock filters available for immediate despatch.**

A1 Microwave has full in house CNC machining, turning, brazing, hard and soft soldering and bending facilities.



Ordering information :- Model number **PB1041WB** Ku-band Satcoms Downconverter Filter

Designed for Ku band satcoms receiver applications for suppression of local oscillator leakage through the mixer and transmitter interference.

Passband	11.7 to 12.2 GHz
Passband insertion loss	1.0 dB max
Passband group delay variation	3.6 nS typical

Rejection :	from DC to 11.5 GHz	60 dB min
	12.4 to 15.5 GHz	50 dB min

Overall length 212 mm nominal

Connectors SMA female (Waveguide alternatives available)

